

Technical Release Notes

Changes to CD Load for COINSAdmin v10.13B

From v10.13B the COINSAdmin CD load has been amended, so that COINS can be deployed on a variable number of CDs, as well as DVD.

Before you can upgrade any COINS environment, you MUST load the software upgrades into the software repository.

This can be done at any time. COINSAdmin may upgrade itself automatically when running this option. This upgrade procedure is fully automated, but you must be aware that if this doesn't occur, the new software will not have been loaded into the repository and you will have to run the same option on the menu again (there are warning messages displayed to notify you of this).

To load the upgrade from CD

Before you load the upgrade, make sure that the commands defined in COINSAdmin Menu Configuration>UNIX Command Maintenance for mounting and un-mounting CDs are correct; they must be named "CD Mount" and "CD Un-Mount"

- 1) Manually Mount the Admin CD to the directory specified by CD Mount Directory: Use the CD Mount command in COINSAdmin System Utilities> Run Command.
- 2) Select Configure COINSAdmin> Load Repository> Load CD Into Repository – this will run COINSAdmin auto-upgrade.
- 3) Repeat Load Repository> Load CD into Repository; this will then prompt for CD1 to be loaded.
- 4) Enter the "root" password- this will unmount the admin CD.
- 5) Place CD1 into the CD-ROM drive and type "y" for "yes".
- 6) Enter the "root" password- this will mount CD1.
- 7) CD1 will then be loaded into software repository.
- 8) Repeat steps 5-7 until all CDs have been loaded.

To load the upgrade from DVD

Before you load the upgrade, make sure that the commands defined in COINSAdmin Menu Configuration>UNIX Command Maintenance for mounting and un-mounting CDs are correct; they must be named "CD Mount" and "CD Un-Mount"

- 1) Manually Mount the Coins DVD to the directory specified by CD Mount Directory: Use the CD Mount command in COINSAdmin System Utilities> Run Command.
- 2) Select Configure COINSAdmin> Load Repository> Load CD Into Repository – this will run COINSAdmin auto-upgrade.
- 3) Repeat Load Repository> Load CD into Repository; this will then prompt for CD1 to be loaded.
- 4) Enter the "root" password
- 5) It will ask you to place CD1 into the CD-ROM drive, obviously no need to do this as only one DVD, just type "y" for "yes".
- 6) Re-enter the "root" password again.
- 7) It will automatically load CD1 (as part of the DVD), which will be loaded into software repository (and displayed in the bottom left corner of the screen).
- 8) Repeat steps 5-7 until all CDs (as part of the DVD) have been loaded.

If you have any questions about the above, please contact the COINS Communications Centre.

Tel: 01753 501025
Fax: 01753 711013
Email: comm.centre@coins-global.com
Web: www.coins-global.com